

# HDDA14 4 Channel Video Distributor

1 IN TO 4 OUT  
VIDEO DISTRIBUTION AMPLIFIER  
FOR TVI, CVI, AHD & 960H FORMATS



## PRODUCT FEATURES

- ◆ Compatible with TVI, CVI, AHD & 960H Formats
- ◆ 1 BNC Input
- ◆ 4 BNC Outputs
- ◆ Included 12 Volt DC Power Supply
- ◆ Built in Surge Protector

## SPECIFICATIONS

SPECIFICATION	HDDA14
Video Format	Compatible with TVI, CVI, AHD & 960H Formats
Video Input	1x Composite BNC
Video Output	4x Composite BNC
Video Input / Output Signal	1vP-P 75 Ohms
Power Requirement	12 Volt DC
Power Supply	Included 12 Volt DC, 500mA
Power Consumption	DC12V / 100mA Max
LED Indicator	Yes - (For Power)
Surge Protector	Yes - Built in 2KV Surge Protector for Power/Video
Dimensions (Including Inputs)	4.7" (W) X 3.7" (H) x 1.2" (D)
Mounting Footprint	4.7" (W) x 2.6" (H)
Operation	Indoor Only
Weight	0.4 lb

\* All specifications subject to change without notice for quality improvement

## VIDEO DISTRIBUTION CABLE CONNECTION

Connect Camera output to HDDA14 video input [BNC]

Connect up to four BNC cables to Video Output [BNC] connections and route to DVR's and/or video monitors.

Insert power supply lead into back of HDDA14.

Plug power supply into wall outlet.

## PACKAGE CONTENTS

- (1) HDDA14 Video Distributor
- (1) 12 Volt DC, 500mA Power Supply
- (1) User Manual



HDDA14 - FRONT



HDDA14 - BACK

## CAMERA DIMENSIONS

